



THE SSC CONTROLS COMPANY

THE FOOT SWITCH EXPERTS®

Product Information Sheet

G-Series Foot Switches – Circuit Diagrams

The G-Series foot switches can include from one to three switches, and up to four independent SPDT circuits. They do not come with cables. The user installs the appropriate cable and strain relief to the switch. G500 models have one switch, G502 models have two switches, G503 models have three switches, and G504 models have four circuits.



For models with two or more switches (G502, G503, or G504), the switches can be independently adjusted. They can be set so one switch goes off before the other or they can be set to go off at the same time. Below are examples of the circuitry of different G-Series foot switches.

Danger: Disconnect input power before performing any installation or maintenance.

Only a qualified electrician should install this foot switch, including proper grounding and installation per local and national electrical codes.

Model	Switch Circuit	Inside of Foot Switch
<p><u>Model Number:</u> G500-MO</p> <p>Circuit: SPDT (single-pole double-throw)</p>		
<p><u>Model Number:</u> G502-MO</p> <p>Circuit: DPDT (double-pole double-throw)</p> <p>Includes two SPDT switches that can be set to activate separately or at the same time.</p>		

The SSC Controls Company
 8909 East Avenue Mentor, Ohio 44060
 Phone: 440 205-1600 Fax: 440 205-1700



THE SSC CONTROLS COMPANY

THE FOOT SWITCH EXPERTS®

<p><u>Model Number:</u> G503-MO</p> <p>Circuit: TPDT</p> <p>(triple-pole double-throw)</p> <p>Includes three SPDT switches that can be set to activate separately or at the same time.</p>		
<p><u>Model Number:</u> G504-MO</p> <p>Circuit: Dual DPDT</p> <p>(two DPDT switches in each unit)</p> <p>Ideal for controlling up to four independent circuits.</p>		
<p><u>Model Number:</u> G500-MO-DB</p> <p>Circuit: SPDT-DB</p> <p>(single-pole double-throw double-break)</p> <p>Also called "Form Z" contacts</p> <p>Double break contacts open and close at two points in the line, enabling the switch to have improved performance in some DC circuits.</p>		

Notes:

- GX-Series are the same as the G-Series, but with a flat cover (they do not have the guard).
- G-Series foot switches are available with other options, such as the Front Gate (-GT models), the Anti-Trip Safety Latch (-AT), Maintained Action (-MA), and two-stage operation (models ending in "-2S). However, the switch circuitry shown above stays the same for these options.
- All foot switches should be properly grounded per local and national electrical codes.

The SSC Controls Company
 8909 East Avenue Mentor, Ohio 44060
 Phone: 440 205-1600 Fax: 440 205-1700